

 Model Number
 DOC NO

 3055D4T
 PERFORMANCE SPECIFICATIONS
 PS3055D4T

 IEPE ACCELEROMETER
 REV.E, EON 12184, 09/21/15



• HERMETICALLY SEALED

- BASE ISOLATED
- IDEAL LOW FREQUENCY RESPONSE
- TEDS

		ENGLISH		SI	
PHYSICAL					_
Weight		0.35	oz	10	grams
Connector	Type	10-32		10-32	
Mounting Provision	Tapped Hole	10-32 X .150 ↓		10-32 X .150 ↓	
Material, Housing/Connector		Titanium		Titanium	
Sensing Element		Ceramic		Ceramic	
Element Style		Planar Shear	•	Planar Shear	
PERFORMANCE					
Sensitivity, ± 5% [1]		50	mV/g	5	mV/m/s ²
Range for ± 5 Volts Output		100	g	981	m/s ²
Frequency Response, ± 10%		1 to 10000	Hz	1 to 10000	Hz
Resonant Frequency		> 36	kHz	> 36	kHz
Broad Band Resolution		0.0010	Grms	0.010	m/s² rms
Linearity [2]		±1	% F.S.	±1	% F.S.
Maximum Transverse sensitivit	ty	5	%	5	%
Strain Sensitivity @ 250με		0.002	g/με	0.02	m/s²/με
ENVIRONMENTAL					
Maximum Vibration		500	Gpeak	4905	m/s² peak
Maximum Shock		2000	Gpeak	19620	m/s² peak
Operating Temperature Range		-60 to +250	°F	-51 to 121	°C
TEDS Operating Temperature		-40 to +185	°F	-40 to +85	°C
Seal		Hermetic	•	Hermetic	
ELECTRICAL					
Supply Current Range [3]		2 to 20	mA	2 to 20	mA
Compliance Voltage Range		18 to +30	Volts	18 to +30	Volts
Output Impedence,Typ		100	Ω	100	Ω
Bias Voltage		11 to 13	VDC	11 to 13	VDC
Discharge Time Constant		0.5 to 1.5	Sec	0.5 to 1.5	Sec
Electrical Isolation		10	GΩ,min	10	GΩ,min
TEDS		IEEE 1451.4		IEEE 1451.4	

This family also includes:							
Model	Sensitivity (mV/g)	Frequency Response (Hz)	Time Constant (Sec)	Operating Temp (°F)			
3055D1T	10	1 to 10000	0.5 to 1.5	-60 to +250			
3055D2T	100	1 to 10000	0.5 to 1.5	-60 to +250			
3055D3T	500	1 to 10000	0.5 to 1.5	-60 to +225			
3055D5T	20	1 to 10000	0.5 to 1.5	-60 to +250			
3055D6T	200	1 to 10000	0.5 to 1.5	-60 to +225			

Refer to the performance specifications of the products in this family for detailed description

Supplied Accessories:

- 1) Accredited calibration certificate (ISO 17025)
- 2) Model 6200 mounting stud, qty 1

Notes:

- [1] Measured at 100Hz, 1 Grms per ISA RP 37.2.
- [2] Measure using zero-based straight line method, % of F.S. or any lesser range.
- [3] Do not apply power to this system without current limiting, 20 mA MAX. To do so will destroy the IC charge amplifier.
- [4] In the interest of constant product improvement, we reserve the right to change specifications without notice.



